




Hand Crimp Tool Operating Instruction And Specifications Sheet

Order No. 64001-0200
Eng. No. RHT 1991
(Replaces 19285-0005)



FEATURES

- A full cycle ratcheting hand tool ensures complete crimps
- Long handles for comfortable crimping with reduced crimping force
- A precision user-friendly terminal locator wire stop holds terminals in the proper crimping position for each of the three nests
- Insulation crimp adjustment allows a precise insulation crimp. To meet or exceed the requirements of UL, CSA and Military Class II
- 3-nested tool eliminates the need for additional tools

SCOPE

InsulKrimp™ Quick Disconnect 10 - 22 AWG.

Testing

Mechanical

The tensile test, or pull test, is a means of evaluating the mechanical properties of the crimped connections. The following charts show the UL specifications for various wire sizes. The tensile strength is shown in pounds and indicates the minimum acceptable force to break or separate the terminal from the conductor.

| Wire Size (AWG) | *UL - 310 |
|-----------------|-----------|
| 22 | 8 |
| 20 | 13 |
| 18 | 20 |
| 16 | 30 |
| 14 | 50 |
| 12 | 70 |
| 10 | 80 |

*UL – 310 – Quick Disconnects

The following is a partial list of the product part numbers and their specifications that this tool is designed to run. We will be adding to this list and an up to date copy is available on www.molex.com

| Wire Size: 14 – 16 AWG 2.00 – 1.30 mm ² | | | | | |
|--|------------------------|-------------------|------|------------------|------|
| Terminal No. | Terminal Eng No. (REF) | Wire Strip Length | | Insul. Dia. Max. | |
| | | In. | mm | In. | mm |
| 19017-0023 | BB-2132 | .312 | 7.94 | .145 | 3.70 |
| 19017-0028 | BB-2135 | .312 | 7.94 | .145 | 3.70 |
| 19017-0031 | BB-2138 | .312 | 7.94 | .145 | 3.70 |
| 19017-0032 | BB-2138-032 | .312 | 7.94 | .145 | 3.70 |
| 19017-0037 | BB-2141 | .312 | 7.94 | .145 | 3.70 |
| 19017-0043 | BB-2191 | .312 | 7.94 | .145 | 3.70 |
| 19017-0044 | BB-2191-032 | .312 | 7.94 | .145 | 3.70 |
| 19019-0022 | BB-8132 | .312 | 7.94 | .138 | 3.50 |
| 19019-0025 | BB-8135 | .312 | 7.94 | .138 | 3.50 |
| 19019-0027 | BB-8138 | .312 | 7.94 | .138 | 3.50 |
| 19019-0028 | BB-8138-032 | .312 | 7.94 | .138 | 3.50 |
| 19019-0034 | BB-8191 | .312 | 7.94 | .138 | 3.50 |
| 19019-0035 | BB-8191-032 | .312 | 7.94 | .138 | 3.50 |
| 19019-0061 | BB-8135-BK | .312 | 7.94 | .138 | 3.51 |
| 19019-0117 | BB-8141 | .312 | 7.94 | .138 | 3.51 |

| Wire Size: 18 – 22 AWG 0.80 – 0.35 mm ² | | | | | |
|--|------------------------|-------------------|------|------------------|------|
| Terminal No. | Terminal Eng No. (REF) | Wire Strip Length | | Insul. Dia. Max. | |
| | | In. | mm | In. | mm |
| 19017-0001 | AA-2131 | .375 | 9.53 | .120 | 3.05 |
| 19017-0005 | AA-2134 | .312 | 7.94 | .135 | 3.40 |
| 19017-0007 | AA-2137 | .312 | 7.94 | .135 | 3.40 |
| 19017-0008 | AA-2137-032 | .312 | 7.94 | .135 | 3.40 |
| 19017-0014 | AA-2140 | .312 | 7.94 | .135 | 3.40 |
| 19017-0018 | AA-2190 | .312 | 7.94 | .135 | 3.40 |
| 19017-0019 | AA-2190-032 | .312 | 7.94 | .135 | 3.40 |
| 19019-0001 | AA-8131 | .343 | 8.73 | .140 | 3.56 |
| 19019-0004 | AA-8134 | .250 | 6.35 | .115 | 2.90 |
| 19019-0006 | AA-8137 | .250 | 6.35 | .115 | 2.90 |
| 19019-0008 | AA-8137-032 | .250 | 6.35 | .115 | 2.90 |
| 19019-0012 | AA-8140 | .250 | 6.35 | .115 | 2.90 |
| 19019-0014 | AA-8190 | .250 | 6.35 | .115 | 2.90 |
| 19019-0015 | AA-8190-032 | .250 | 6.35 | .115 | 2.90 |
| 19019-0118 | AA-8134-BK | .250 | 6.35 | .115 | 2.90 |

| Wire Size: 10 – 12 AWG 5.00 – 3.30 mm ² | | | | | |
|--|------------------------|-------------------|------|------------------|------|
| Terminal No. | Terminal Eng No. (REF) | Wire Strip Length | | Insul. Dia. Max. | |
| | | In | mm | In. | mm |
| 19002-0044 | C-5265 | .312 | 7.94 | .245 | 6.22 |
| 19017-0047 | C-2143 | .375 | 9.53 | .250 | 6.40 |
| 19019-0037 | C-8143 | .375 | 9.53 | .225 | 5.70 |

| Wire Size: 10 – 12 AWG 5.00 – 3.30 mm ² | | | | | |
|--|------------|-------------------|------|------------------|------|
| Terminal No. | Terminal | Wire Strip Length | | Insul. Dia. Max. | |
| | | In | mm | In. | mm |
| 19025-0005 | CMCT-5 | .375 | 9.53 | .225 | 5.70 |
| 19606-0005 | 19606-0005 | .375 | 9.53 | .120 | 3.05 |

OPERATION

Open the tool by first closing the jaws sufficiently for the ratchet mechanism to release.

Crimping Terminals

1. There are 2 Tab Locator Blades supplied with the tool. One is for .187 and .250 Tabs; the other is for .205 Tabs and .110 Tabs. Make sure the proper blade is installed on the top of the locator and the other is stored on the bottom of the locator.
2. Push the terminal onto the Tab Locator all the way to the stop in the proper color-coded nest. The Barrel of the terminal should be up (See Figure 1).
3. Partially close the tool to hold the terminal in place (See Figure 2).




Figure 1




Figure 2




Figure 3

4. Insert the properly stripped wire into the terminal barrel (See Figure 2 and 3). The wires end should butt against the wire stop stamped into each terminal. Cycle the tool.

Note: The tamper proof ratchet action will not release the tool until it has been fully closed.

5. Remove the crimp and inspect for proper crimp location, and check for insulation closure. Molex offers a Crimp Inspection Handbook for closed barrel industrial product. See our website or contact your sales engineer.

6. If the insulation part of the crimp needs to be adjusted, first loosen the M4 screw on the bottom tool jaw, then insert a 3/32 hex wrench (supplied) into the bottom of the lower die (See Figure 4). A clockwise (CW) rotation decreases insulation crimp while a counter-clockwise (CCW) rotation increases insulation crimp. After adjusting retighten the M4 screw.

Note: Whenever crimping without the locator, make sure the seam of the terminal is oriented up or down in the tool if using unbrazed product, as this will provide higher pull force values.

Maintenance

It is recommended that each operator of the tool be made aware of, and responsible for, the following maintenance steps.

1. Remove dust, moisture and other contaminants with a clean brush, or soft, lint-free cloth.
2. Do not use any abrasive materials that could damage the tool.
3. Make certain all pins; pivot points and bearing surfaces are protected with a thin coat of high quality machine oil. Do not oil excessively. The 64001-0200 (RHT-1991) was engineered for durability, but like any fine piece of equipment it needs cleaning and lubrication for a maximum service life of trouble-free crimping. A light oil, such as 30 weight automotive oil used at the oil points shown in Figure 4, every 5,000 crimps or 3 months will significantly enhance the tool life and ensure a stable calibration.
4. When tool is not in use, keep the handles closed to prevent objects from becoming lodged in the crimping dies, and store the tool in a clean, dry area.




Figure 4

Miscrimps or Jams

Should this tool ever become stuck or jammed in a partially closed position, **Do Not force the handles open or closed.** The tool will open easily by pressing the ratchet release lever (See Fig.5).

How To Adjust Tool Preload (See Fig. 5)

Over the life of the tool, it may be necessary to adjust tool handle preload force. Listed below are the steps required to adjust the crimping force of the hand tool to obtain proper crimp conditions:





Figure 5

1. Remove the screw and plastic cover washer. Note the setting wheel position.
2. Lift the setting wheel off the axle. Turn the eccentric axle with a screwdriver.
3. Turning the eccentric axle counter-clockwise will increase handle force.
4. Replace the setting wheel to the axle, aligning the nearest notch in the setting wheel to the dowel pin.
5. Replace the plastic cover washer and screw.
6. Check the crimp specifications after tool crimp force is adjusted.

Tool Calibration

A Certificate of Calibration (see last page) was supplied with the tool. To recalibrate this tool, pin gauge measurements should be taken in each conductor nest and compared to this chart. The tool should be lubricated prior to recalibration to ensure consistent measurements. Handle preload is factory set to 25-45 LBS. See How to Adjust Tool Preload (see Figure 5) to recalibrate.



| Nest Color Code | Wire Range | | "X" Dimension Conductor Crimp | | | Crimp Inspection Marking |
|-----------------|------------|-----------------|----------------------------------|------|-------|-----------------------------|
| | AWG | mm ² | Mean | Go | No Go | |
| Red | 18 - 22 | 0.35 - 0.80 | .069 | .066 | .072 | oo |
| Blue | 14 - 16 | 1.30 - 2.00 | .092 | .089 | .095 | o |
| Yellow | 10 - 12 | 3.30 - 5.00 | .100 | .097 | .103 | oo |

Warranty

This tool is for electrical terminal crimping purposes only. This tool is made of the best quality materials. All vital components are long-life tested. All tools are warranted to be free of manufacturing defects for a period of 30 days. Should such a defect occur, we will repair or exchange the tool free of charge. This repair or exchange will not be applicable to altered, misused or damaged tools. This tool is designed for hand use only. Any clamping, fixturing, or use of handle extensions voids this warranty.

Hand held crimping tools are intended for low volume, prototyping, or repair requirements only.

Caution: Repetitive use of this tool should be avoided.

PARTS LIST

| Item | Order No | Description | Quantity |
|-------------------------|-------------------|--|-----------------|
| | 64001-0200 | Hand Crimp Tool | (Fig. 6) |
| 1 | 64000-0076 | Repair Kit (Springs, Pins and E-Rings) | 1 |
| 2 | 63810-0000 | Handle | 1 |
| 3 | 64001-0275 | Locator Assembly | 1 |
| 4 | 64001-0270 | Tooling Kit | 1 |
| Tooling Kit Only | | | |
| 5 | 64001-0214 | Conductor Punch | 1 |
| 6 | 64001-0212 | Conductor Anvil | 1 |
| 7 | 64001-0215 | Insulation Punch | 1 |
| 8 | 64001-0113 | Insulation Anvil | 1 |
| 9 | N/A | 4 mm Dia. by 5.0 mm Lg. Roll Pins | 2** |
| 10 | N/A | #10-32 by 5/16" Lg. Cup Pt. Set Screw | 1** |

** The following purchased parts are available from an Industrial supply company such as MSC (1-800-645-7270).





Figure 6



Certificate of Calibration

Tool Order Number _____

Tool Eng. Number _____

Tool Revision _____

Serial Number _____

Date of Manufacture _____

Handle Load Range at 1 inch from the Tips = _____

Actual = _____

Pin Gauge of Conductor Nest/Nests or Slug height if the nest is the "F" Crimp style.

Range Conductor Nest # 1 = _____ -- Actual = _____

Range Conductor Nest # 2 = _____ -- Actual = _____

Range Conductor Nest # 3 = _____ -- Actual = _____

Technician _____

Date of Calibration _____

Calibration should be done every 5,000 cycles or 3 months.

Tools should be lubricated during this operation.

Molex Application Tooling Group

1150 E. Diehl Road

Naperville, IL 60563

Tel: (630) 969-4550

Fax (630) 505-0049