



**Tripp Lite**  
1111 West 35th Street  
Chicago, IL 60609 USA  
Telephone: + (773) 869 1234  
E-mail: [saleshelp@tripplite.com](mailto:saleshelp@tripplite.com)

## Model #: SU10000RT3U2TF

**SmartOnline Expandable Rack/Tower UPS System - Online, double-conversion protection for mission-critical applications**

### Highlights



- 10,000VA / 10kVA online 10U rack / tower UPS with expandable runtime (3U Power Module + 3U Battery Pack + QTY 2 -2u stepdown transformers)
- Manual Bypass Switch and detachable PDU enables hot-swap UPS replacement without powering off connected loads
- Maintains 208V and simultaneous 120V output
- 2% output voltage regulation over an input voltage range of 156 to 276
- Enhanced serial communications ports, SNMP/Web Card Slot and EPO interfaces
- \$250,000 Ultimate Lifetime Insurance (USA & Canada only).

### Description

10,000 VA on-line, double-conversion UPS system for critical server, network and telecommunications equipment. Installs in only 10 rack spaces (3U power module, 3U battery pack and two 2U step-down transformers). Maximum installed rack depth of 32.5 in. Expandable battery runtime with optional BP240V10RT3U external battery packs. Full-time sine wave 208V and 120V +/-2% output. Actively converts raw incoming AC power to DC, then re-converts output back to completely regulated, filtered AC output. Operates continuously without using battery power during brownouts to 156V and overvoltages to 276V. Standard 3-wire 208V hardwire input connection; NEMA L6-30R, L6-20R and 5-15/20R output receptacles. Detachable input-output PDU module with manual bypass switch enables hot-swap UPS replacement without disrupting power to connected equipment. Network-grade AC surge and noise suppression. Zero transfer time between AC and battery operation. Network management interfaces support communications via RS-232, contact-closure port and optional SNMPWEBCARD slot. Supports detailed monitoring of equipment load levels, self-test data and mains power conditions via network interfaces. Includes PowerAlert monitoring software and complete cabling. Emergency Power Off (EPO) interface. Front panel LEDs offer at-a-glance confirmation of line power status, battery power status, AC-to-DC conversion, DC-to-AC conversion, bypass mode and output power status. LED/LCD display panel easily rotates for better viewing in rackmount or tower configurations. LCD panel with scroll buttons offers detailed diagnostic test information at startup and during self tests, plus real-time data on input and output voltage, frequency (Hz), load percentage and battery charge level. Audible alarm. Self-test. Fault-tolerant auto-bypass mode. 4-post rackmount accessories and 2-9USTAND tower kit included; 2POSTRMKITWM two post rackmount hardware accessories available. Field-replaceable, hot-swappable power module and external battery 2-year warranty and \$250,000 [connected equipment insurance](#); extended warranty and service contracts available.

### Applications

Ideal for protection of sensitive electronics in any application calling for upright tower or 19-in. rackmount UPS protection. Common applications include any mix of servers, workstations, hubs, routers, concentrators, IP telephony and traditional PBX switching systems

### Package Includes

- 3U power module with detachable hot-swap PDU input/output panel and manual bypass switch
- 3U external battery pack
- 2 x 2U step-down transformers
- Two sets of 4-post rackmount rails (one for each 3U component); one set of tower stands for upright tower installation
- PowerAlert Software, complete data cabling, user manual with warranty information

Features

- 10,000 VA on-line, double-conversion UPS system (high voltage input/high AND low voltage output)
- Detachable input-output PDU module with manual bypass switch enables hot-swap UPS replacement without powering off connected equipment
- Installs in only 10 rack spaces (3U power module, 3U battery pack, 2 x 2U step-down transformers) with a maximum installed depth of 32.5 inches
- Offers 4 min. runtime at full load (10,000VA/8000W) and 10 min. at half load (5000VA/4000W). Runtime is expandable with any number of optional BP240V10RT3U external battery packs
- Full-time sine wave 208V and simultaneous 120v +/-2% output
- Actively converts raw incoming AC power to DC, then re-converts output back to completely regulated, filtered AC output
- Operates continuously without using battery power during brownouts to 156V and overvoltages to 276V
- Standard 3-wire 208V hardwire input connection
- 2 NEMA L6-30R, 4 L6-20R and 24 5-15/20R output receptacles
- Detailed LCD panel with scroll buttons offers detailed diagnostic test
- Network-grade AC surge and noise suppression
- Zero transfer time between AC and battery operation
- Includes slot for internal SNMP/web card, plus DB9 enhanced serial monitoring port, and contact closure port for unattended shutdown, remote control and monitoring of UPS system and power data
- Supports detailed monitoring of equipment load levels, self-test data and mains power conditions via network interfaces. Includes PowerAlert monitoring software and complete cabling
- Emergency Power Off (EPO) interface
- Front panel LEDs offer at-a-glance confirmation of line power status, battery power status, AC-to-DC & DC-to-AC conversion, bypass mode and output power status.
- Fault-tolerant auto-bypass mode prevents loss of output during UPS fault conditions or excessive UPS loading
- 4-post rackmount and upright tower installation accessories included; 2POSTRMKITWM 2-post rackmount hardware accessories available
- Field-replaceable, hot-swappable power module and external battery packs
- Attractive all-black color scheme
- 2-year warranty; \$250,000 [connected equipment insurance](#)
- Extended warranty and service contracts available

Specifications

SYSTEM OVERVIEW	
Voltage compatibility	208V & 120V AC
Frequency compatibility	50/60 Hz
OUTPUT	
Output VA	10000
Output watts	8000
Output nominal voltage	208V & 120V AC
Output voltage regulation	Maintains pure sine wave output at all times, regulated within 2% of selected nominal output voltage, less than 3% total harmonic distortion when used with computer loads
Output frequency regulation	Regulates line frequency to 50/60Hz +/- 0.05Hz
Outlet quantity / type	2 x NEMA L6-30R, 4 x NEMA L6-20R, 24 x NEMA 5-15/20R
INPUT	
Maximum input amps	208V- 44.9A
Input connection type	Hardwire
BATTERY	
Full load runtime	4 min. (10,000VA/8000W)
Half load runtime	10 min. (5000VA/4000W)
Connects to UPS via	Included 3-wire DC cable

<b>DC system voltage</b>	240VDC
<b>Typical battery lifespan</b>	4-6 years
<b>Battery recharge rate</b>	Less than 8 hours to 90% (included battery set only)
<b>VOLTAGE REGULATION</b>	
<b>Voltage regulation description</b>	On-line, double-conversion process give this UPS the ability to maintain output voltage within +/-2% of selected nominal voltage at all times
<b>Overvoltage correction</b>	Maintains continuous operation without using battery power during overvoltages to 276V AC, regulating output within 2% of selected nominal
<b>Brownout correction</b>	Maintains continuous operation without using battery power during brownout / undervoltage conditions to 156V AC, regulating output within 2% of selected nominal
<b>LEDS ALARMS &amp; SWITCHES</b>	
<b>Front panel LEDs</b>	6 LED DISPLAY: line power, bypass, inverter, charger, output AC and battery operation. LED/LCD display panel easily rotates for better viewing in rackmount or tower configurations.
<b>Alarms</b>	Multi-function audible alarm offers notification of UPS start, backup operation, low battery, overload, UPS fault, inverter fault, DC bus fault, overtemperature, remote shutdown, shutdown imminent and shutdown complete
<b>Switches</b>	Includes main power off/on switch, plus 2 switches to set and execute scrollable LCD functions
<b>SURGE / NOISE SUPPRESSION</b>	
<b>AC suppression response time</b>	Instantaneous
<b>EMI / RFI AC noise suppression</b>	Yes
<b>PHYSICAL</b>	
<b>Shipping weight (lbs)</b>	402
<b>Shipping weight (kg)</b>	181
<b>Shipping Dimensions (HWD/in)</b>	49.3 x 23 x 31.5
<b>Shipping Dimensions (HWD/cm)</b>	125.1 x 58.4 x 80
<b>Unit weight (lbs)</b>	Power Module (54.8), Step-down Transformers (60), Battery Pack (158.7)
<b>Unit weight (kg)</b>	Power Module (24.7), Step-down Transformers (27), Battery Pack (71.4)
<b>Unit Dimensions (HWD/in)</b>	Power Module 5.14 x 17.5 x 25, Step down transformers 3.5 x 17.5 x 20.8, Battery Pack 5.16 x 17.5 x 25 (Installed depth of power module extends to 32.5 inches once detachable PDU backplate is installed)
<b>Unit Dimensions (HWD/cm)</b>	Power Module 13.3 x 44.4 x 63.5, Step down transformers 8.9 x 44.5 x 52.7, Battery Pack 13.4 x 40.6 x 63.5 (Installed depth of power module extends to 82.6 cm once detachable PDU backplate is installed)
<b>Material of construction</b>	Steel
<b>Form factors supported</b>	Rack (10U)
<b>Cooling method</b>	Fan
<b>Battery Access</b>	User replaceable, hot swappable external battery pack
<b>ENVIRONMENTAL</b>	
<b>Operating Temperature</b>	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius
<b>Storage Temperature</b>	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius
<b>Relative Humidity</b>	0 to 95%, non-condensing
<b>Line mode BTU/hr. (Max.)</b>	3022 btu/hr.
<b>Battery mode BTU/hr. (Max.)</b>	3022 btu/hr.

COMMUNICATIONS	
Network monitoring port	Includes 2 built-in DB9 monitoring ports (1-RS232 / 1-contact closure)
Software and cabling included	Includes PowerAlert UPS monitoring software for all common network and standalone operating systems. Cabling included.
SNMP compatibility	Built-in accessory slot accommodates internal SNMP / Web card and other network accessories
WatchDog compatibility	Yes, compatible with Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application / OS or hard power off/on reboot of connected equipmentideal for unattended kiosk applications
LINE / BATTERY TRANSFER	
Transfer time from line power to battery mode	Zero; on-line UPS continuously converts incoming AC to DC, then back to AC. When line power is interrupted, UPS maintains continuous output from battery reserves with absolutely no disruption in output AC power.
Low voltage transfer to battery power	Maintains continuous operation during undervoltages as low as 156VAC. Below this point, output is maintained utilizing battery reserves.
High voltage transfer to battery power	Maintains continuous operation during overvoltages to 276V AC. Above this point, output is maintained utilizing battery reserves.
SPECIAL FEATURES	
EPO port	Includes dedicated EPO (emergency power off) interface and cabling
Cold Start	Yes, inverter can be cold started to enable temporary AC output during a power failure
Appearance	Attractive all-black color scheme
BATTERY PACK ACCESSORY (optional)	
Battery Pack Accessory (optional)	BP240V10RT3U
CERTIFICATIONS	
Certifications	Tested to UL1778 (USA), CSA C22.2 No. 107.3 (Canada), CE (European Union), NOM (Mexico), Class A (Emissions)
WARRANTY	
Product warranty	2 years
Connected equipment insurance (USA and Canada Only)	\$250,000
Optional coverage	3-year, 5-year, next-day and on-site warranty coverage available for select opportunities; contact Tripp Lite

## Related Items

<b>Extended Warranties</b>		
WEXT3-SU10K	3-Year Extended Warranty - For SU10K models	Qty: [optional]
WEXT5-SU10K	5-Year Extended Warranty - For SU10K models	Qty: [optional]

<b>External Battery Packs</b>		
BP240V10RT3U	External Battery Pack and Cable. 3U, Expandable, Black 3-Point Connector	Qty: [optional]
BP240V557C-1PH	External battery pack for use with select Tripp Lite UPS Systems	Qty: [optional]
BP240V787C-1PH	External battery pack for use with select Tripp Lite UPS Systems	Qty: [optional]
BP240V1407C-1PH	External battery pack for use with select Tripp Lite UPS Systems	Qty: [optional]
BP240V1037C-1PH	External battery pack for use with select Tripp Lite UPS Systems	Qty: [optional]

<b>Rackmount/Wallmount Kits</b>		
2POSTRMKITWM	Allows for 2 post mounting of Tripp Lite 2U-4U rackmount UPS systems and battery packs	Qty: [optional]

<b>Shutdown Cable Kits</b>		
----------------------------	--	--

AS400CABLE KIT	Power Management Tools - UPS Communication Cable Kit for System i / AS400 / iSeries Servers	Qty: [optional]
<b>SNMP Accessories</b>		
ENVIROSENSE	Power Management Tools - Environmental Sensor	Qty: [optional]
SNMPWEBCARD	Power Management Tools - Internal SNMP/Web Card	Qty: [optional]
<b>Start-Up/Warranty Services</b>		
W02-BW0	Regular business hours start-up, excludes on-site warranty.	Qty: [optional]
W02-BW2-1BD	Regular business hours start-up and two year on-site, next business day break/fix warranty service for locations within 350 miles of a covered service area.	Qty: [optional]
W02-BW2-247	Regular business hours start-up and two year on-site, 24-by-7 break/fix warranty service for locations within 250 miles of a covered service area.	Qty: [optional]
W02-BW3-1BD	Regular business hours start-up and three year on-site, next business day break/fix warranty service for locations within 350 miles of service area.	Qty: [optional]
W02-BW3-247	Regular business hours start-up and three year on-site, 24-by-7 break/fix warranty service for locations within 250 miles of service area.	Qty: [optional]
W02-EW0	Evening or weekend hours start-up, excludes on-site warranty.	Qty: [optional]
W02-EW2-1BD	Evening or weekend hours start-up and two year on-site, next business day break/fix warranty service for locations within 350 miles of service area.	Qty: [optional]
W02-EW2-247	Evening or weekend hours start-up and two year on-site, 24-by-7 break/fix warranty service for locations within 250 miles of service area.	Qty: [optional]
W02-EW3-1BD	Evening or weekend hours start-up and three year on-site, next business day break/fix warranty service for locations within 350 miles of service area.	Qty: [optional]
W02-EW3-247	Evening or weekend hours start-up and three year on-site, 24-by-7 break/fix warranty service for locations within 250 miles of service area.	Qty: [optional]
W02-BW1-1BD	Regular business hours start-up and one year on-site, next business day break/fix warranty service for locations within 350 miles of a covered service area.	Qty: [optional]
W02-BW1-247	Regular business hours start-up and one year on-site, 24-by-7 break/fix warranty service for locations within 250 miles of a covered service area.	Qty: [optional]
W02-EW1-1BD	Evening or weekend hours start-up and one year on-site, next business day break/fix warranty service for locations within 350 miles of service area.	Qty: [optional]
W02-EW1-247	Evening or weekend hours start-up and one year on-site, 24-by-7 break/fix warranty service for locations within 250 miles of service area.	Qty: [optional]

More information, including related products, owner's manuals, and additional technical specifications, can be found online at [www.tripplite.com/EN/products/model.cfm?txtModelID=3213](http://www.tripplite.com/EN/products/model.cfm?txtModelID=3213).