

951

Low-Solids No-Clean Flux Pen®

Product Description

Kester 951 is a halogen-free, non-rosin organic Flux Pen® that is specifically designed for rework of conventional and surface mount circuit board assemblies. The extremely low solids content (2.0%) and nature of the activator system results in practically NO RESIDUE left on the assembly after soldering. There are no residues to interfere with electrical testing. Kester 951 exhibits improved soldering performance to minimize solder bridges (shorts) during rework operations. This flux is suitable for automotive, computer, telecommunications and other applications where reliability considerations are critical. The surface insulation resistance on soldered boards is higher than that provided by typical organic water-soluble fluxes. Kester 951 contains a corrosion inhibitor such that no corrosion products are formed when bare copper surfaces are exposed to humid environments.

Performance Characteristics:

- Improves soldering performance
- Eliminates the need and expense of cleaning
- Non-corrosive tack-free residues
- Classified as ORL0 per J-STD-004
- Compliant to Bellcore GR-78

Physical Properties

Specific Gravity: 0.789 ± 0.003

Antoine Paar DMA 35 @ 25°C

Percent Solids (theoretical): 2.0

Acid Number (typical): 14.3 mg KOH/g of flux

Tested by potentiometric titration

Reliability Properties

Copper Mirror Corrosion: Low

Tested to J-STD-004, IPC-TM-650, Method 2.3.32

Corrosion Test: Low

Tested to J-STD-004, IPC-TM-650, Method 2.6.15

Silver Chromate: Pass

Tested to J-STD-004, IPC-TM-650, Method 2.3.33

Chloride and Bromides: None Detected

Tested to J-STD-004, IPC-TM-650, Method 2.3.35

Fluorides by Spot Test: Pass

Tested to J-STD-004, IPC-TM-650, Method 2.3.35.1

SIR, IPC (typical): Pass

Tested to J-STD-004, IPC-TM-650, Method 2.6.3.3

	<u>Blank</u>	<u>951</u>
Day 1	$2.3 \times 10^{10} \Omega$	$9.4 \times 10^9 \Omega$
Day 4	$1.3 \times 10^{10} \Omega$	$7.8 \times 10^9 \Omega$
Day 7	$9.8 \times 10^9 \Omega$	$6.3 \times 10^9 \Omega$

Application Notes

Flux Application:

Kester 951 is applied to circuit boards via Flux Pen® for rework of printed wire assemblies.

Process Considerations:

Kester 951 should only be applied to areas that will be fully heated by the soldering iron or other reflow tool. Care should be taken to avoid flooding the assembly. The surface tension has been adjusted to help the flux form a thin film on the board surface allowing rapid solvent evaporation.

Cleaning:

Kester 951 flux residues are non-conductive, non-corrosive and do not require removal in most applications.

Storage and Shelf Life:

Kester 951 is flammable. Store away from sources of ignition. Shelf life is 2 years from date of manufacture when handled properly and held at 10-25°C (50-77°F).

Health & Safety:

This product, during handling or use, may be hazardous to health or the environment. Read the Material Safety Data Sheet and warning label before using this product.

World Headquarters: 800 W. Thorndale Avenue, Itasca, Illinois, 60143 USA

Phone: (+1) 847-297-1600 • **Email:** customerservice@kester.com • **Website:** www.kester.com

Asia Pacific Headquarters

500 Chai Chee Lane
Singapore 469024
(+65) 6449-1133
customerservice@kester.com.sg

European Headquarters

Zum Plom 5
08541 Neuensalz
Germany
(+49) 3741 4233-0
customerservice@kester-eu.com

Japanese Headquarters

20-11 Yokokawau 2-Chome
Sumida-Ku
Tokyo 130-0003 Japan
(+81) 3-3624-5351
jpsales@kester.com.sg

The data recommendations presented are based on tests, which we consider reliable. Because Kester has no control over the conditions of use, we disclaim any responsibility connected with the use of any of our products or the information presented. We advise that all chemical products be used only by or under the direction of technically qualified personnel who are aware of the potential hazards involved and the necessity for reasonable care in their handling. The technical information contained herein is consistent with the properties of this material but should not be used in the preparation of specifications as it is intended for reference only. For assistance in preparing specifications, please contact your local Kester office for details.