

Feedthrough components **FN 761X**

I III SCHAFFNEC energy efficiency and reliability



- EN/IEC 60939 approval
- Rated currents from 10 to 250A
- 5kV pulse test capability
- Class Y2 capacitor

Approvals


RoHS



Technical specifications

······		
Maximum continuous operating voltage:	300VAC, 50/60Hz (ENEC)	
	250VAC, 50/60Hz (UL)	
	1000VDC max.	
Rated currents:	10 to 250A @ 60°C max.	
Capacitor class:	Y2	
High potential test voltage:	3000VDC for 2 sec	
Insulation resistance (100VDC after 60 sec):	< 0.33μF, R > 15,000MΩ	
	> 0.33μF, τ > 5000s	
Temperature range (operation and storage):	-40°C to +100°C (40/100/21)	
Flammability corresponding to:	UL 94V-2 or better	
MTBF @ 60°C/300V (Mil-HB-217F):	< 200A: > 675,000 hours	
	> 200A' > 494 000 hours	

Typical electrical schematic



Feedthrough filters offer a high insertion loss across a broad band of frequencies from a few tens of kHz up to the GHz region. In general, feedthrough filters offer a higher level of EMI suppression than feedthrough capacitors of the same current rating. This is particularly relevant to applications where source impedance is smaller than 50Ω . Different versions are available offering a wide selection on operating currents and performance levels. AC feedthrough filters are designed and approved for up to 300VAC50/60Hz operation.

Features and benefits

- Very low internal series inductance.
- Very high self-resonant frequency.
- Self-healing dielectric.
- High quality and reliability.
- Through-bulkhead mounting.
- Anti-twist protection.
- Custom-specific or dual-versions on request.

Typical applications

- Power line filter for 110/240VAC power lines
- Increasing system and information security
- Power supplies
- Switching and cellular equipment
- Computer servers
- UPS power supplies
- Medical equipment
- Shielded rooms

Feedthrough selector table

Feedthrough	Rated current @ 60°C	Leakage current* @ 250VAC/50Hz	Capacitance** C	Inductance L @ 10kHz	DC resistance*** R @ 25°C	Weight
	[A]	[mA]	[nF]	[nH]	[mΩ]	[g]
FN 7611-10-M3	10	1.89	10	70	1.2	55
FN 7612-10-M3	10	8.86	47	70	1.52	70
FN 7611-16-M4	16	4.15	22	70	0.65	80
FN 7612-16-M4	16	18.85	100	70	0.92	90
FN 7611-32-M4	32	4.15	22	70	0.65	80
FN 7612-32-M4	32	18.85	100	70	0.92	90
FN 7611-63-M6	63	28.3	150	186	0.47	250
FN 7612-63-M6	63	88.6	470	124	0.53	500
FN 7612-100-M8	100	188	1000	124	0.23	750
FN 7611-250-M12	250	88.6	470	169	0.23	1086

* Tolerance +20%

** Tolerance ±20%

*** Tolerance +15%

Typical filter attenuation


Full load, 50Ω system

10A types

dB	П	тш		m	m	<u> </u>	П	Π	m	<u> </u>	п	П	Ш	Ш		П	1	m	m
90		111			Ш		Н	Щ	Ш	-	Н	#	II,	₩	_	,	l		Щ
80-		Ш			Ш		Ш	Ш			Ш		n	Ш	Δ	ľ	ý		Ш
		Ш						Ш			h	١I	ŀ	ł	11	li I	1		
70		111			Ħ		Ħ	Ħ	T	17	Ħ	Ŵ	Ħ	Ň		Ť	Ħ	T	Π
60		++++			₩		H	₩	Щ	Ł	И	4	Н	⋕	\vdash	Н	H	H	Н
50		Ш			Щ		Щ	Щ	X		Ľ	#	Щ	₩	i	Ц	Щ		Щ
40		Ш					Ш	lk	1	Ľ	Ш		Ш	Ш					
		Ш				B		И		1				II					
30		111			III	10	17	Ħ	H)	ľ	Ħ	t	Ħ	III		Η	Ħ	Π	П
20		++++			Н	r	Ĥ	∦	И	-	Н	╢		₩	-	Н	H		Н
10-		Ш		И	Ш		1	Ш			Ц	1		Щ	_				Щ
		Ш	Ł		łľ	1													
10	Dk		100 k		1	М			10	M			10	00	м			1	G

A = FN 7612-10-M3 B = FN 7611-10-M3

100A types



A = FN 7612-100-M8

16A types

A = FN 7612-16-M4 B = FN 7611-16-M4

250A types

dB	<u> </u>		TTTTT	_	тп	т		п	п	m	_		П	m		т	ΤТ	TTT
90-		Ш				Ш						1	И	Ш		Ш		Ш
		Ш			Ш				k	h		1		Ш				
80-		11			111	III		Π	1		ſ	Ħ	Π	II		Π	ll	Ш
70		+#		+	₩	╫	A	И	t		1	H	Н	╫	-	H	₩	₩
60				_	╢	╢		Ĥ	+		¢	\mathbb{H}	Щ	₩	-	\mathbb{H}	⋕	Ш
50		Ш	Ш		Ш	Щ	/	Ц	1	Ш		Ц	Ш	Ш		Ц	Ш	Ш
		Ш			Ш		V							Ш				
40		Ш			Ш	III		Π	T			Π	Π	II		Π	T	Ш
30		Ħ		7	椚	H		Η	t	III		H	Ħ	Ħ	-	H	Ħ	₩
20	\vdash	Щ	H	-	₩	₩		Н	╫			\mathbb{H}	Н	₩	⊢	\mathbb{H}	₩	₩
10		11	Ш		Ш	Щ		Ц	1	Ш		Щ	Щ	Щ		Щ	Щ	Щ
	ΓI												Ш	II				
10	٦k		100	۱k		1	М			10	M		1	0	nм		-	16

A = FN 7611-250-M12

32A types

dB					
90					
80				$\square \square$	
70			IIIIK V	/ALA [V.
60			IIM A	I W V	
50			////		
40		A B	ЛШИТ		
30		в/	1111/1		
20			11		
10					
۳Ц	#1-1	1111			
10 k	100 k	1M	10 M	100 M	1G


A = FN 7612-32-M4 B = FN 7611-32-M4


63A types

dB				MIL	
90				W	
				1/111	
80			IN. N	/	
70			H M M Y I	41111	
60					
		A B	MIIN VI		
50		H B /	YHHE H		
40		IIII k	1111		
		HΠΥ			
30		14-1			
20		1			
	14/11				
10	11111				
РШ					
10 k	100 k	1M	10 M	100 M	1G

A = FN 7612-63-M6 B = FN 7611-63-M6

Mechanical data





Panel cut out

Dimensions

	Α	В	C	D	E	L	М	Ν	S	Т
FN 7611-10-M3	107	12	20	17	16	66	10.3	Ø12.3	M3	M12x1
FN 7612-10-M3	140	12	20	17	16	99	10.3	Ø12.3	M3	M12x1
FN 7611-16-M4	116	14	25	22	18	69	14.3	Ø16.3	M4	M16x1
FN 7612-16-M4	148	14	25	22	18	101	14.3	Ø16.3	M4	M16x1
FN 7611-32-M4	116	14	25	22	18	69	14.3	Ø16.3	M4	M16x1
FN 7612-32-M4	148	14	25	22	18	101	14.3	Ø16.3	M4	M16x1
FN 7611-63-M6	173	16	32	27	26	105	18.3	Ø20.3	M6	M20x1
FN 7612-63-M6	189	19	54	41	26	118	24.3	Ø27.3	M6	M27x1.5
FN 7612-100-M8	227	19	54	41	32	144	24.3	Ø27.3	M8	M27x1.5
FN 7611-250-M12	267	19	54	41	46	160	29.3	Ø32.3	M12	M32x1.5
Tolerances					±2		±0.2			

All dimensions in mm; 1 inch = 25.4mm

Tolerances according: ISO 2768-m / EN 22768-m

Recommended torque

	M3	M4	M6	M8	M12	M12x1	M16x1	M20x1	M27x1.5	M32x1.5
Terminal thread	0.5Nm	1.2Nm	2.5Nm	5Nm	11Nm					
Mounting thread						3Nm	4Nm	7Nm	12Nm	14Nm