

PC924X

OPIC Photocoupler

OPIC Photocoupler for IGBT Drive of Inverter

■ Features


- (1) Built-in direct drive circuit for IGBT drive
(I_{O1P}, I_{O2P} : 0.4 A)
- (2) High speed response
(t_{PHL}, t_{PLH} : MAX. 2.0 μ s)
- (3) Wide operating supply voltage range
(V_{CC} : 15 to 30 V, T_a = -10 to 60 °C)
- (4) High noise reduction type
(CM_H = MIN. -1 500 V/ μ s)
(CM_L = MIN. 1 500 V/ μ s)
- (5) High isolation voltage ($V_{iso(rms)}$: 5 kV)

■ Applications

- (1) IGBT drive for inverter control

■ Outline Dimensions

(Unit : mm)



* "OPIC" (Optical IC) is a trademark of the SHARP Corporation.
An OPIC consists of a light-detecting element and signal-processing circuit integrated onto a single chip.

■ Absolute Maximum Ratings

(Unless specified, $T_a = T_{opr}$)

Parameter	Symbol	Ratings	Unit
Input			
Forward current	I_F	25	mA
*1 Reverse voltage	V_R	6	V
Supply voltage	V_{CC}	35	V
Output			
O1 Output current	I_{O1}	0.1	A
*2 O1 Peak output current	I_{O1P}	0.4	A
O2 Output current	I_{O2}	0.1	A
*2 O2 Peak output current	I_{O2P}	0.4	A
O1 Output voltage	V_{O1}	35	V
Power dissipation	P_O	500	mW
Total power dissipation	P_{tot}	550	mW
*3 Isolation voltage	$V_{iso(rms)}$	5.0	kV
Operating temperature	T_{opr}	-20 to +80	°C
Storage temperature	T_{sg}	-55 to +125	°C
*4 Soldering temperature	T_{sol}	260	°C

*1 $T_a = 25^\circ\text{C}$

*2 Pulse width $\leq 0.15 \mu\text{s}$, duty ratio = 0.01

*3 40 to 60%RH, AC for 1 minute, $T_a = 25^\circ\text{C}$

*4 For 10s

(Notice) • In the absence of device specification sheets, SHARP takes no responsibility for any defects that may occur in equipment using any SHARP device shown in catalogs, data books, etc. Contact SHARP in order to obtain the latest device specification sheets before using any SHARP device.
• Specifications are subject to change without notice for improvement.

(Internet) • Data for SHARP's optoelectronic/power device is provided for internet. (Address <http://www.sharp.co.jp/ecg/>)

Electro-optical Characteristics

(Unless specified, Ta=Topr)

Parameter			Symbol	Conditions	MIN.	TYP.	MAX.	Unit
Input	Forward voltage		V _{F1}	T _a = 25 °C, I _F =20 mA	—	1.2	1.4	V
			V _{F2}	T _a = 25 °C, I _F = 0.2 mA	0.6	0.9	—	V
	Reverse current		I _R	T _a = 25 °C, V _R = 4 V	—	—	10	μA
	Terminal capacitance		C _t	T _a =25 °C, V= 0, f= 1 kHz	—	30	250	pF
Output	Operation temperature supply voltage		V _{CC}	T _a = -10 to 60 °C	15	—	30	V
				—	15	—	24	V
	O ₁ low level output voltage		V _{O1L}	V _{CC1} =12 V, V _{CC2} = -12 V, I _{O1} = 0.1 A, I _F = 10 mA	—	0.2	0.4	V
	O ₂ high level output voltage		V _{O2H}	V _{CC} =V _{O1} = 24 V, I _{O2} = -0.1 A, I _F = 10 mA	18	21	—	V
	O ₂ low level output voltage		V _{O2L}	V _{CC} = 24 V, I _{O2} = 0.1 A, I _F = 0	—	1.2	2.0	V
	O ₁ leak current		I _{O1L}	T _a = 25 °C,V _{CC} =V _{O1} = 35 V, I _F =0 mA	—	—	500	μA
	O ₂ leak current		I _{O2L}	T _a = 25 °C,V _{CC} =V _{O2} = 35 V, I _F =10 mA	—	—	500	μA
	High level supply current		I _{CCH}	T _a =25 °C, V _{CC} = 24 V, I _F = 10 mA	—	6	10	mA
				V _{CC} = 24 V, I _F = 10 mA	—	—	14	mA
	Low level supply current		I _{CCL}	T _a =25 °C, V _{CC} = 24 V, I _F = 0 mA	—	8	13	mA
				V _{CC} = 24 V, I _F = 0 mA	—	—	17	mA
Transfer characteristics	"Low→High" thresh hold input current *5		I _{FLH}	T _a =25°C, V _{CC} = 24 V	1.0	4.0	7.0	mA
				V _{CC} = 24 V	0.6	—	10.0	mA
	Isolation resistance		R _{ISO}	T _a = 25 °C, DC= 500 V 40 to 60 %RH	5 x 10 ¹⁰	1 x 10 ¹¹	—	Ω
	Response time	"Low→High"transfer time	t _{PLH}	T _a = 25 °C, V _{CC} = 24 V,I _F = 10 mA, R _G = 47 Ω, C _G = 3000 pF	—	1.0	2.0	μs
		"High→Low"transfer time	t _{PHL}		—	1.0	2.0	
		Rise time	t _r		—	0.2	0.5	
		Fall time	t _f		—	0.2	0.5	
	Instantaneous common mode rejection voltage "Output:High level"		CM _H	T _a =25 °C, V _{CM} =600 V _(peak) , I _F =10 mA V _{CC} = 24 V, ΔV _{O2H} = 2.0 V	-1 500	—	—	V/μs
	Instantaneous common mode rejection voltage "Output: Low level"		CM _L	T _a =25 °C, V _{CM} =600 V _(peak) , I _F = 0 mA V _{CC} = 24 V, ΔV _{O2L} = 2.0 V	1 500	—	—	V/μs

*5 I_{FLH} is forward current when output become "Low" to "High"

*6 When measuring output and transfer characteristics, connect a by-pass capacitor(0.01μF or more) between V_{CC} and GND near the device.

Truth Table

Input	O ₂ output	Tr. 1	Tr. 2
ON	High level	ON	OFF
OFF	Low level	OFF	ON

NOTICE

- The circuit application examples in this publication are provided to explain representative applications of SHARP devices and are not intended to guarantee any circuit design or license any intellectual property rights. SHARP takes no responsibility for any problems related to any intellectual property right of a third party resulting from the use of SHARP's devices.
- Contact SHARP in order to obtain the latest device specification sheets before using any SHARP device. SHARP reserves the right to make changes in the specifications, characteristics, data, materials, structure, and other contents described herein at any time without notice in order to improve design or reliability. Manufacturing locations are also subject to change without notice.
- Observe the following points when using any devices in this publication. SHARP takes no responsibility for damage caused by improper use of the devices which does not meet the conditions and absolute maximum ratings to be used specified in the relevant specification sheet nor meet the following conditions:
 - (i) The devices in this publication are designed for use in general electronic equipment designs such as:
 - Personal computers
 - Office automation equipment
 - Telecommunication equipment [terminal]
 - Test and measurement equipment
 - Industrial control
 - Audio visual equipment
 - Consumer electronics
 - (ii) Measures such as fail-safe function and redundant design should be taken to ensure reliability and safety when SHARP devices are used for or in connection with equipment that requires higher reliability such as:
 - Transportation control and safety equipment (i.e., aircraft, trains, automobiles, etc.)
 - Traffic signals
 - Gas leakage sensor breakers
 - Alarm equipment
 - Various safety devices, etc.
 - (iii) SHARP devices shall not be used for or in connection with equipment that requires an extremely high level of reliability and safety such as:
 - Space applications
 - Telecommunication equipment [trunk lines]
 - Nuclear power control equipment
 - Medical and other life support equipment (e.g., scuba).
- Contact a SHARP representative in advance when intending to use SHARP devices for any "specific" applications other than those recommended by SHARP or when it is unclear which category mentioned above controls the intended use.
- If the SHARP devices listed in this publication fall within the scope of strategic products described in the Foreign Exchange and Foreign Trade Control Law of Japan, it is necessary to obtain approval to export such SHARP devices.
- This publication is the proprietary product of SHARP and is copyrighted, with all rights reserved. Under the copyright laws, no part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, for any purpose, in whole or in part, without the express written permission of SHARP. Express written permission is also required before any use of this publication may be made by a third party.
- Contact and consult with a SHARP representative if there are any questions about the contents of this publication.