



GENERAL SPECIFICATIONS FOR PUSH-PULL PUSHBUTTONS

Electrical Capacity (Resistive & Inductive Load)

Power Level: Shown in the following tables

Other Ratings

Contact Resistance: 10 milliohms maximum Insulation Resistance: 200 megohms minimum @ 500V DC Dielectric Strenath: 1,500V AC min. for 1 minute min. Mechanical Life: 30,000 operations minimum

> **Electrical Life:** 10,000 operations minimum Total Travel: .177" (4.5mm) for SB862;

.059" (1.5mm) for SB282 -10°C through +70°C **Operating Temp Range:**

(+14°F through +158°F)

Materials & Finishes

Brass with nickel plating Plunger: Brass with nickel plating **Bushing:** Case: Phenolic resin

Case Cover: Steel with zinc plating **Movable Contactor:** Brass with silver plating - SB862;

copper with silver plating - SB282 **Movable & Stationary Contacts:** Silver - SB862;

> copper with silver plating - SB282 Terminals: Brass with silver plating - SB862;

copper with silver plating - SB282

Note: Terminal numbers are

SINGLE POLE PUSH-PULL WITH SOLDER LUG												
			Pushbutton Position/Connected Terminals () = Momentary				Electrical Capacity (Resistive)					
Model	Approvals	Pole & Throw	Normal	Keyway	Down	1	AC 125V	AC 250V				
SB862		SPST	ON	1-2	OFF	_	10A	5A				


SPST not on the switch. Schematic:


- Standard Hardware: AT504M Knurled Nut, AT508 Lockwasher, AT527M Hex Backup Nut. See Accessories & Hardware section for details.
- Solder lug terminal hole accommodates one 12-gauge solid or stranded wire.


Throw &



Supplied with Black Knob AT424A










Panel Thickness .205" (5.2mm)

DOUBLE POLE PUSH-PULL WITH SOLDER LUG

			Pushbuttor	Position/Con	nected Termi	Electrical Capacity (Resistive)		
Model	Approvals	Pole & Throw	Normal	Keyway	Down	•	AC 125V	AC 250V
SB282		DPDT	ON	2-1 5-4	ON	2-3 5-6	6A	3A

Throw & **Schematic:**

DPDT





Note: Terminal numbers are actually on the switch.


- Standard Hardware: AT504M Knurled Nut, AT508 Lockwasher, AT527M Hex Backup Nut. See Accessories & Hardware section for details.
- Solder lug terminal hole accommodates one 12-gauge solid or stranded wire.



Supplied with Black Knob AT423A; Red Knob AT423C **Available on Request**









Panel Thickness .272" (6.9mm)