Unit in mm

TOSHIBA Photocoupler GaAs Ired & Photo-MOS FET

# **TLP176G**

Modems In PC Modem-Fax Cards

**Telecommunictions** 

The TOSHIBA TLP176G consists of gallium arsenide infared emitting diode optically coupled to a photo–MOS FET in a SOP, which is suitable for surface mount assembly.

The TLP176G is suitable for the modem applications which require space savings.

• Peak off-state voltage: 350V (min)

• Trigger LED current: 3mA (max)

• On–state resistance:  $35\Omega$  (max)

• Isolation voltage: 1500Vrms (min)

• UL recognized: UL1577, file No. E67349

• BSI approved

: BS EN60065: 1994,certificate No.8273 BS EN60950: 1992,certificate No.8274


• SEMKO approved: SS EN60065

SS EN60950

• Option(V4)type

TUV approved: DIN VDE0884 / 06.92,

Certificate No.R9850580




Weight: 0.1 g

TOSHIBA


**JEDEC** 

EIAJ


#### Pin Configuration (top view)



: Anode
 : Cathode
 : Drain
 : Drain



#### **Schematic**



### **Maximum Ratings (Ta = 25°C)**

	Characteristic	Symbol	Rating	Unit
	Forward current	ΙF	50	mA
	Forward current derating (Ta ≥ 25°C)	ΔI <sub>F</sub> / °C	-0.5	mA / °C
LED	Pulse forward current (100µs pulse,100pps)	I <sub>FP</sub>	1	Α
	Reverse voltage	$V_{R}$	5	V
	Junction temperature	Tj	125	°C
	Off-state output terminal voltage	V <sub>OFF</sub>	350	V
Detector	On-state current	I <sub>ON</sub>	120	mA
Dete	On–state current derating (Ta ≥ 25°C)	Δl <sub>ON</sub> / °C	-1.2	mA / °C
	Junction temperature	Tj	125	°C
Total power dissipation		PT	350	mW
Total power dissupation derating(Ta ≥ 25°C)		ΔPT / °C	-0.35	mW / °C
Storage temperature range		T <sub>stg</sub>	-55~125	°C
Operating temperature range		T <sub>opr</sub>	-40~85	°C
Lead	Lead soldering temperature(10 s)		260	°C
Isolation voltage (AC,1 min., R.H.≤ 60%) (Note 1)		BVS	1500	Vrms

(Note 1): Device considered a two-terminal device: Pin 1 and 2 shorted together and pin 3 and 4 shorted together.

# **Recommended Operating Conditions**

Characteristic	Symbol	Min.	Тур.	Max.	Unit
Supply voltage	$V_{DD}$	_	_	280	V
Forward current	I <sub>F</sub>	5	7.5	25	mA
On-state current	I <sub>ON</sub>	_	_	100	mA
Operating temperature	T <sub>opr</sub>	-20	_	65	°C

# Individual Electrical Characteristics (Ta = 25°C)

Characteristic		Symbol	Test Condition	Min.	Тур.	Max.	Unit
	Forward voltage	$V_{F}$	I <sub>F</sub> = 10mA	1.0	1.15	1.3	V
LED	Reverse current	I <sub>R</sub>	V <sub>R</sub> = 5V	_	_	10	μΑ
	Capacitance	C <sub>T</sub>	V = 0,f = 1MHz	_	30	-	pF
Detector	Off-state current	l <sub>OFF</sub>	V <sub>OFF</sub> = 350V	_	_	1	μΑ
	Capacitance	C <sub>OFF</sub>	V = 0,f = 1MHz	_	40	-	pF

### **Coupled Electrical Characteristics (Ta = 25°C)**


Characteristic	Symbol	Test Condition	Min.	Тур.	Max.	Unit
Trigger LED current	I <sub>FT</sub>	I <sub>ON</sub> = 120mA	_	1	3	mA
On-state resistance	R <sub>ON</sub>	I <sub>ON</sub> = 120mA,I <sub>F</sub> = 5mA	_	22	35	Ω


### Isolation Characteristics (Ta = 25°C)


Characteristic	Symbol	Test Condition	Min.	Тур.	Max.	Unit
Capacitance input to output	CS	V <sub>S</sub> = 0,f = 1MHz	_	0.8	_	pF
Isolation resistance	R <sub>S</sub>	V <sub>S</sub> = 500V,R.H ≤ 60%	5×10 <sup>10</sup>	10 <sup>14</sup>		Ω
		AC, 1minute	1500	_		Vrms
Isolation voltage	$BV_S$	AC, 1second (in oil)	_	3000	-	VIIIIS
		DC, 1minute (in oil)	_	3000		Vdc


# **Switching Characteristics (Ta = 25°C)**


Characteristic	Symbol	Test Condition	Min.	Тур.	Max.	Unit
Turn-on time	t <sub>ON</sub>	R <sub>L</sub> = 200Ω	_	0.3	1	ms
Turn-off time	t <sub>OFF</sub>	$V_{CC}$ = 20V, $I_F$ = 5mA	_	0.1	1	1113



































2002-09-25

6

#### **RESTRICTIONS ON PRODUCT USE**

000707EBC

- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property. In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc..
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk.
- Gallium arsenide (GaAs) is a substance used in the products described in this document. GaAs dust and fumes
  are toxic. Do not break, cut or pulverize the product, or use chemicals to dissolve them. When disposing of the
  products, follow the appropriate regulations. Do not dispose of the products with other industrial waste or with
  domestic garbage.
- The products described in this document are subject to the foreign exchange and foreign trade laws.
- The information contained herein is presented only as a guide for the applications of our products. No
  responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other
  rights of the third parties which may result from its use. No license is granted by implication or otherwise under
  any intellectual property or other rights of TOSHIBA CORPORATION or others.
- The information contained herein is subject to change without notice.